

SPECIFICATION SHEET

SA300 Series Zip-Set™ DIGITAL TIMER

APPLICATIONS

- Automatically turn ON/OFF outdoor lighting.
- Save energy. Turn ON adjusts to sunset daily. No need to run lights all day & night.
- Provide all-night security.

FEATURES

SCHEDULING:

Choose sunset or 7 day timer modes.

- Zip-Set™ turns lights ON at sunset & OFF at countdown or preset time.
- 7 day weekly programming. 7-5-2 settings for full week, weekdays, and weekends.
- Option to set with one of three ON/OFF programs.

EASY SET-UP:

Fast programming with Zip-Set™ One-Step™ set-up. Just enter your area code.

DAYLIGHT SAVINGS:

Manual adjustment.

RANDOM SETTING:

Give the 'lived in' look as times are varied each day.

POWER OUTAGE BACKUP:

Battery back-up for power outages.
Supplied with two CR2032 batteries.

OVERRIDE:

Manual ON/TIMER switch.

COLOR:

Grey.

MOUNTING:

SA300 Series: Indoor surface mount.
SA400: Indoor/outdoor surface mount.

WIRING:

Terminal Range #8 - #16AWG.

INPUT VOLTAGE:

SA300 Series: 120VAC 60 Hz.
SA400: 120/277VAC 60 Hz.



SA400

SA300

ORDERING INFO

CAT. NO.	UPC CODE	INPUT SUPPLY (VAC) 60Hz	COLOR
SA300	16546	120	SPST
SA306	16549	120	DPST
SA400	16552	120/277	SPST

CONTACT RATINGS

TYPE	VOLTAGE (VAC)	RATING
Resistive	120*	40A
Inductive	120*	40A
Tungsten	120*	40A
Incandescent	120*	40A
Motor	120	11/2HP
SA400	120/277	-

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>