

# Wireless Outlet Dimmer

Looks Small, Thinks Big

The Wireless Outlet Dimmer connects to household plug-in lamps, immediately making them part of the home automation system and enabling quick and easy configuration. Its dual-capacity dimmer allows users to independently dim two lights from the single unit. From the living room floor light to the bedroom table lamp, the Wireless Outlet Dimmer adds intelligent, automated features to just about any dimmable plug-in lights.

It's all part of the Control4 vision. We bring the benefits of a truly automated home to more people with solutions that are affordable, easy to install and designed to adapt to any home or lifestyle.



## Features and Benefits

### Smart Design

- **Low profile** — Small form factor fits easily behind furniture.
- **Dual outlets** — Two dimmable outlets give added flexibility.

### Easy To Install and Use

- **Wireless** — No special cables to pull through the home.
- **Easy recognition** — Just plug it in, press a button, and it's immediately recognized.
- **Easily controllable** — Immediately controllable from Control4 Keypads, Touch Screens, or System Remote Control.

### Intelligent From Front To Back

- **Built-in dimmer capabilities** — Dim lamps for a romantic dinner or set bedroom lamps to gradually turn on in the morning.
- **Anytime control** — Adjust the room's brightness level based on the time of day.
- **Anywhere control** — Intelligent, reliable, wireless connectivity using the ZigBee™ (802.15.4) mesh networking standard.
- **Energy Efficient** — By automating plug-in devices, electricity is only used when needed.

**Dim** the floor lamps in the living room when your house goes to sleep. In the morning **gently light** your children's bedroom with light from a table lamp. **Ramp** up the desk lamp in the den as you enter the room.

Control

# Wireless Outlet Dimmer



## Technical Specifications

### Model Number

- LOZ-5D1-W

### Load Capacity

- 700 Watts total across both outlets

### Load Type

- Incandescent
- Tunsten-Halogen

### Communications

- Wireless ZigBee (802.15.4) mesh networking

### Environmental

- Operational 0°C to 40°C
- Humidity 5% to 95% Non-Condensing
- Storage -20°C to 70°C

### Power Requirements

- 120 VAC, 50/60 Hertz, 1.7 W

### Dimensions & Weight

- H x W x D: 4.5" x 2.6" x 1.6" (115mm x 67mm x 42mm)
- Weight: 8.0 oz (227 g)

### Available Colors

- White

## Related Control4 Products

In addition to the Wireless Outlet Dimmer, Control4 offers:



Wireless Outlet Switch — A controllable switch for plug-in devices rated up to 1000 VA.



Wireless Switch — For new or retrofit home automation solutions using ZigBee wireless connectivity.

Control4 

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>